

Ingress high pass filter - plug-in module

- For LHD / NVD to prevent Ingress distortion jamming on return path
- Style JXP 1", 3-PIN

Type	NHP 12-1	NHP 15-1	NHP 18-1
Item No.	57002815	57002116	57002814
Application	LHD / NVD	LHD / NVD	LHD / NVD
Frequency range Upstream MHz	12-204	15-204	18-204
Stopp band MHz	0.1-10	0.1-13	0.1-15
Through loss dB	0.4	0.4	0.4
Stopp band isolation dB	> 40	> 40	> 40
Dimensions / Weight mm / kg	8 x 28 x 4 / 0.01	8 x 28 x 4 / 0.01	8 x 28 x 4 / 0.01


Bandpass Filter

Type	BPF 18-65
Item No.	57003192
Frequency range Upstream MHz	18...65
Through loss dB	0.4
Stopp band Isolation dB	
f < 13 MHz LP	> 45
f = 13...15 MHz LP	> 20
f = 85...120 MHz HP	> 20
f > 120 MHz HP	> 45
Dimensions / Weight mm / kg	9 x 28 x 4 / 0.01

other frequencies on request

ATTENUATION JXP-PADS

- Fix attenuation-PAD's
- 1 dB step values for gain and slope adjustment
- Plastic cover for solid protection
- Length 1" available



Type	PAD 0	PAD 1	PAD 2	PAD 3	PAD 4	PAD 5	PAD 6
Item No.	10161523	10161524	10161525	10161526	10161527	10161528	10161529
Loss dB	0	1	2	3	4	5	6
Type	PAD 7	PAD 8	PAD 9	PAD 10	PAD 11	PAD 12	PAD 13
Item No.	10161530	10161531	10161532	10161533	10161534	10161535	10161536
Loss dB	7	8	9	10	11	12	13
Type	PAD 14	PAD 15	PAD 16	PAD 17	PAD 18	PAD 19	PAD 20
Item No.	10161537	10161538	10161539	10161540	10161541	10161542	10161543
Loss dB	14	15	16	17	18	19	20

Length 25.4 mm (1")